



МАРТ

Е-МАРТ  
ВАШ ПОСТАВЩИК  
ZKTECO


<https://emart.su/brands/zkteco/>

Федеральный	8 800 511-77-41
Санкт-петербург	8 812 426-99-66
Москва	8 495 137-99-67
Краснодар	8 861 205-62-66

[www.emart.su](http://www.emart.su)

[mail@emart.su](mailto:mail@emart.su)

# KR500 Series



KR500-E/M



KR501-E/M



KR502-E/M



KR503-E/M

## RFID/Mifare Card Readers

### Read Range

KRxxx-E: Up to 10CM

KRxxx-M: Up to 5CM

### Reading Time

≤200ms

### Input Port

External LED Control

External Buzzer Control

### Output Format

KRxxx-E: 26bit Wiegand (Default)

KRxxx-M: 34bit Wiegand (Default)

### Power/Current

DC 6-14V / Max.70mA

### LED

Red and Green LEDs

### Operating Temperature

-20°C to 65°C(-10° to +70°C)

### Material

ABS+PC with texture

### Operating Humidity

10% to 90% relative humidity

non-condensing

### Beeper

Yes

### Index of Protection

KR500-E/M: IP65

KR501-E/M: IP65

KR502-E/M: IP64

KR503-E/M: IP65

## Dimensions

	KR500 E/M	KR501 E/M	KR502 E/M	KR503 E/M
<b>Height:</b>	7.8cm	8.6cm	7.8cm	11.6cm
<b>Depth:</b>	1.6cm	1.6cm	2.6cm	1.6cm
<b>Width:</b>	4.4cm	8.6cm	4.4cm	7.5cm
<b>Weight:</b>	50g	110g	150g	120g

### ZKTeco Inc.

ZK Mansion, Wuhe Rd, Gangtuo, Bantian, Buji Town,  
Longgang District, Shenzhen China 518129

Tel: 86-755-8960 2345/46/47/48

E-mail: sales@zkteco.com

www.zkteco.com

### Global Offices:

USA: +1 732-412-6007

EU: +34 916532891

Brazil: +55 31 2515-8326

Thailand: +66-027199154

Mexico: +52-55-52928418

South Africa: +27 12 259 1047

Egypt: +201110444134

Dubai: +971 4 6091 310

India: +91 8123536788

Indonesia: +62 21 2921 8949

Vietnam : +84-0169-5813007

Philippines: +63 9084118832

Russia: +8 915 178-46-81